

Features & Benefits

- Selectable mode of operation either 0-10V or 0-20mA
- 12 bit resolution
- Simple, quick installation
- Easy configuration via USB/downlink
- Battery life 3+ years*
- Signal and battery indicator

Technical Overview

Voltage (0-10V) or Current (0-20mA) is converted to LoRaWAN so the device data can be displayed and analysed.

Technical Specification

Radio output type	LoRaWAN
Frequency Range	863-870MHz, 902-928MHz
Security	AES 128 encryption
Batteries	SAFT LS14500 or EVE ER14505 AA size 3.6 Volt Lithium Thionyl Chloride (Li-SOCl2) batteries (non-rechargeable) or direct equivalent
Battery Life	3+ Years
Housing colour	Black
Housing Dimensions	129 x 67 x 41mm
IP Rating	IP40 / NEMA 1. Optional gasket: IP67 / NEMA 4
Compliance	UKCA, CE, FCC compliant
Country of origin	UK

Related Product Codes

RF-LW-VC-IN	LoRaWAN Voltage and Current converter

Tel: +44 (0)1732 861200 | E-mail: sales@sontay.com | Web: www.sontay.com

Sontay Limited. Four Elms Road, Edenbridge, Kent, TN8 6AB UK

© 2023 Sontay Limited. All rights reserved. Whilst every effort has been made to ensure the accuracy of this specification, Sontay cannot accept responsibility for damage, injury, loss or expense from errors or omissions. In the interest of technical improvement, this specification may be altered without notice.

This document is uncontrolled if printed, all information is subject to change. Generated on 16/09/24